


F01570

# WAY-FI PLUS P.S.U. DIN8 32VDC-3.5A

## DESCRIPTION

### Connection terminals

- L, N: AC input.
- LED: power indicator.
- BUS(IM): connection terminal for indoor monitors.
- BUS(DS): outdoor panels connection terminal.

### Wiring and installing the power supply

1. Fix the DIN rail to the wall with screws.
2. Pull the mounting bracket, and hang the unit on the DIN rail.
3. Remove the AC cover and connect the AC cable (L, N).
4. Connect the wiring to the entrance panel and the indoor monitor.
5. After connecting the AC cable, you need to replace the cover.

## TECHNICAL SPECIFICATIONS

### Specifications

- AC input current: 100V~240V, 2A, 50Hz/60Hz.
- DC output current: 32±2V, 3.5A.
- Dimensions 140(W) x 97.5(H) x 58.5(D) (without wall bracket).
- Installation method DIN rail mounting (8 DIN modules).
- Includes overcurrent and short-circuit protection.

**Technology:** WAYFI PLUS

**Weight:** 0.496 kg

**Measures of the packed product:** 7x19,8x10,9 cm

**EAN 13:** 8424299015705