

F05250

RF BASIC-2B RECEIVER 12-24V

DESCRIPTION

- Autonomous receiver supplied by 12/24Vac/dc that allows to manage up to 500 codes from 868Mhz RF transmitters.
- A channel (emitter pushbutton) can activate one or another relay, or both relays at the same time.
- It allows to opening remotely pedestrian or vehicular doors through a remote control up to 100 metres.
- The receiver also allows a manual programming or via radio programming.
- The receiver includes 2 relays as standard: one configured as monostable and the second relay configured as monostable=impulse or bistable via a jumper (imp/bis) in the same receiver.
- Monostable=impulse activates the relay during 2 seconds per each pulse of the emitter.
- Bistable. Relay is activated and the relay is deactivated per each pulse of the emitter.

TECHNICAL SPECIFICATIONS

ENVIRONMENTAL	
Operating temperature (ºC)	[-20,85]
MECHANICAL	
Product dimensions (height x width x depth) (mm)	74 x 63 x 25
ELECTRICAL	
Minimum consumption (W)	1.44
Maximum power consumption (W)	2.16
ADDITIONAL DETAILS	
Weight (kg)	0.201
Packaging measurements (height x width x depth) cm	4,5x8,4x18,5
EAN	8424299052502

ACCESSORIES



F05231

KEYSINGLE PLUS2 REMOTE CONTROL



F05232

KEYSINGLE PLUS4 REMOTE CONTROL



F05259

RF KEYSINGLE MINI REMOTE CONTROL



F04800

P.S.U DIN4 230VAC/12VAC - 1,5A



F04813

P.S.U. DIN6 100-240VAC/12VDC-2A