Product Code

F94421

# 2W CITY VEO WIFI DUOX+ KIT

Reference

94421

EAN

8424299944210

## Description.

Description

Fermax presents the new **VEO WIFI DUOX PLU**S kits for single-family houses, offices and businesses .

The kits include all the necessary materials for its installation: CITYLINE entrance panel, VEO WIFI monitor and power supply.

In addition, they work with DUOX PLUS, a fully digital door entry and video door entry system and technology on two non-polarized wires, which simplifies their installation while maintaining the highest quality in the product and design,

They include the VEO WIFI DUOX PLUS monitor as standard, equipped with a Wi-Fi connection that allows calls to be forwarded to mobile devices .
Thanks to the Fermax DuoxMe application , available for free in the Play Store and App Store, the video door entry functions can be managed directly from a mobile or tablet, to connect to your home, wherever you are. By connecting your WiFi DUOX PLUS monitors with the DuoxMe app, a range of possibilities will open up. Of all of them we highlight two that will be key: Divert calls from the video door entry unit to your mobile and open the door to the house from a distance.

They also come as a standard with the Photocaller feature, which automatically captures an image of the caller. If the user decides to activate this function, the monitor stores up to 150 images, indicating the date and time when they were taken. When the maximum capacity has been reached, taking a new photo will erase the first one stored. The screen always indicates if there are photos not displayed or if the date / time are not configured.

The VEO WIFI DUOX PLUS monitor is made of high impact ABS plastic.
Includes a 4.3" widescreen color display (16: 9).
The unique and exclusive design of the handset incorporates a magnet that makes it easy for the user to position it, ensuring a correct hanging at the end of the conversation.
Its balanced design of pure lines is distinctive, modern and minimalist.

DUOX PLUS is the new digital technology that exceeds all expectations. Because it makes the difficult easy.

Technical Details

Includes:

- 40008 CITY DUOX PLUS 2/L plate. S1: 130x128
- 8948 S1 built-in box: 115x114x45
- 9446 VEO DUOX PLUS WIFI Monitor 4.3” (x2)
- 9447 DUOX PLUS connector (x2)
- 4826 Power supp. unit+filter DIN6 24VDC-1.5A
- 4802 Power supply DIN4 230VAC/12VAC-1A
- 3255 DUOX PLUS line adapter

Video:

- Sensor: 1/3" color CMOS.
- Effective pixels > 340K. (camera captures 720x480)
- Minimum external lighting: 0 lux. Since it has LEDs, no additional lighting is required.
- S/N >45dB.
- Frame rate 25 fps.
- Resolution > 368x288 pixels.
- Video Codec: H264 Highline Profile
- Auto iris.
- Auto BLC.
- Viewing angle 120º horizontal, 80º vertical.
- Fisheye correction.
- Color night vision through white LEDs.
- Pan & Tilt digital zoom.

## Details.

| Weight (kg) | Packaging measurements (height x width x depth) cm | Video Door Entry system Technologie |
|---|---|---|
| 3.024275 | 23x23,7x18,2 | DUOX |

Manuals

- 970048b_Config_VOZ_Placas_Puls_VIDEO_DUOX_Plus_V07_22.pdf

- 970338b Guia rapida kits DUOX PLUS unificada V05_26.pdf

## Products included

F08948
CITY FLUSH BOX FOR KIT (S1)

F40008
CITY PANEL DUOX PLUS S1 CP201

F09447
DUOX PLUS CONNECTOR

F03255
DUOX PLUS LINE ADAPTOR

F09446
DUOX PLUS VEO WIFI 4.3" MONITOR

F04802
P.S.U. DIN4 230VAC/12VAC-1A

F04826
POWER SUPP. UNIT+FILTER DIN6 24VDC-1.5A

## Accessories

F08851
CITY FLUSH BOX S1

F09191
CITY PANEL S1 MODULAR DECORATIVE FRAME

F07061
CITY S1 SURFACE BOX

F08378
CITY SINGLE ANGLE BOX S1

F08400
CITY SINGLE HOOD S1

F08251
CITYLINE DECORATIVE FRAME S1

F09444
DUOX PLUS CAMERA INTERFACE

F03267
DUOX PLUS RELAY

F02040
ELECTRONIC EXTENSION CALL

F03389
UNIVERSAL FRAME LARGE

F02438
VDS LIGHT/BUZZER ACTIVATOR

F09410
VEO MONITOR DESKTOP SUPPORT

F03443
VEO TELEPHONE HANDSET W/INDUCT.LOOP